



Specifications Ledvance LED Tube T8 Performance (EM/Mains) High Output 6.8W  
1100lm - 840 Cool White | 60cm - Replaces 18W - Motion Sensor

[View Product](#)

## General Information

|                         |                                               |
|-------------------------|-----------------------------------------------|
| SKU                     | 248112                                        |
| EAN                     | 4099854044472                                 |
| Manufacturer Code       | 4099854044472                                 |
| Brand                   | Ledvance                                      |
| Manufacturer Name       | LED TUBE T8 EM MOTION SENSOR P 600mm 6.8W 840 |
| Full box quantity       | 10                                            |
| Budgetlight warranty    | 5 Years                                       |
| Energy efficiency class | C                                             |
| Average Lifetime (h)    | 60000                                         |
| Voltage (V)             | 220-240                                       |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED             |
| Replaces (Watt)             | 18              |
| Wattage                     | 6.8W            |
| Dimmable                    | Not Dimmable    |
| Cap/base                    | G13             |
| Rotatable                   | No              |
| Colour Code                 | 840 Cool White  |
| Colour temperature (Kelvin) | 4000 Cool White |
| Colour Rendering (Ra)       | 80-89           |
| Colour of Light             | White           |

|                       |               |
|-----------------------|---------------|
| Light colour options  | Single Color  |
| Luminous Flux (Lumen) | 1100lm        |
| Lumen per watt        | 161           |
| Power factor          | >0.90         |
| Product Type Category | LED Tube T8   |
| Type of sensor        | Motion Sensor |

## Lamp Information

|                      |                                                                       |
|----------------------|-----------------------------------------------------------------------|
| LED Starter included | Yes                                                                   |
| Requires Ballast     | No                                                                    |
| Ballast              | Conventional – there is a starter, Mains – Directly connected to 230V |
| LED Tube Output      | Standard Output                                                       |
| Bulb finish          | Frosted                                                               |
| Housing              | Glass                                                                 |
| Product Serie        | Performance                                                           |

## Dimensions

|               |      |
|---------------|------|
| Length        | 60cm |
| Length (mm)   | 603  |
| Diameter (mm) | 26.7 |
| Exact shape   | T8   |

## Why Budgetlight?



Guaranteed **budget prices**



Up to **7 years warranty**



**Easy** return process



Long-life **LED solutions**